

- 4 REMOVE AND SALVAGE EXISTING TYPE 25 ELECTROLIER AND SIGNAL HEAD. R/C EXISTING FOUNDATION AND PULL BOX. REMOVE CONDUCTORS AND ABANDON CONDUIT.



03340.12.046

84 of 104

9

T1.6

N= NEW CONDUIT
E= EXIST CONDUIT
GENERAL NOTES:

- | POLE AND EQUIPMENT SCHEDULE | | | | | | | | | | | |
|-----------------------------|----------------------------------|-------------------|-----------------------------------|---|-------------------------|-------------------|------|----------------|-----------------|-------|--|
| POLE NO | TYPE OF POLE | LUMINAIRE | VEHICLE SIGNAL | | | PEDESTRIAN SIGNAL | | | PED PUSH BUTTON | | REMARKS |
| | | VOLTAGE/AMPS | NO. | TYPE | MOUNTING (F/I) | NO. | TYPE | MOUNTING (F/I) | Ø | ARROW | |
| 1 | 1-A | | 62 | 3S12" | TV-1-T | | | | | | REMOVE AND SALVAGE EXIST POLE AND SIGNAL HEAD. R/C FOUNDATION. SEE NOTE 3 SHEET T-2. |
| 2 | 1-A | | 22
65
31 | 3S12"
3S12"
4S12" GRAVOLA | TV-3-T | | | | | | REMOVE AND SALVAGE EXIST POLE AND SIGNAL HEADS. R/C FOUNDATION. SEE NOTE 3 SHEET T-2. |
| 3 | PPP | | | | | | | | 6 | | F/I PEDESTRIAN PUSHBUTTON POST AND PUSHBUTTON ASSEMBLY |
| 4 | TYPE 25 | | 21 | 3S12" | SV-1-T | | | | | | REMOVE AND SALVAGE STREET LIGHT POLE & SIGNAL EQUIPMENT. R/C FOUNDATION. SEE NOTE 3 SHEET T-2. |
| 5 | 17-3-100
W/20' MA | | 21
24 | 4S12" GRA
4S12" GRA | SV-1-T
MAT | | | | | | #2 4 SECTION (RT)
ADDED LOUVERS |
| 6 | 4-A
TYPE 15 TS | 120V/
150W | 13-93
25
141+OLB
142+OLB | 3S12" LA(PV)
3S12" | SV-2-T
SV-2-T | | | | | | #1 PV
ADDED LOUVER |
| 7 | 19-4-100
W/25' MA | 120V/
150W | 61+OLB
62+OLB
44 94 | 3S12"(PV)
3S12"(PV)
3S12" LA(PV) | SV-1-T
NAS
MAT | | | | | | #1 PV, OLB PV |
| 8 | TYPE 15 TS |
120V/
150W | 67+OLB | 3S12"(PV) | SV-1-T | | | | | | OLB PV |
| 9 | 1-A | | 32
61
109+OLB
103+OLB | 3S12"
3S12" | TV-2-T | | | | | | REMOVE AND SALVAGE EXIST SIGNAL EQUIPMENT. R/C FOUNDATION & PULL BOX. SEE NOTE 3 SHEET T-2. |
| 10 | 19-3-100
W/30' MA |
120V/
150W | 20+OLA
23+OLA
103+OLA | 3S12"(PV)
3S12"(PV)
3S12"(PV) MAS | SV-1-T
MAS MAS | 49 | | SP-1-T | 4 | | #2 + OLA, F/I R17 NO LEFT TURN SIGN |
| 11 | MISSION BAY
STYLE | | 65 | 3S12" | SV-1-T | 48 | | SP-1-T | 4 | | |
| 12 | MISSION BAY
STYLE
W/40' MA | | 81
84 | 3S12"
3S12" | SV-1-T
MAT | 69 | | SP-1-T | 6 | | F/I SNS "MARIPOSA ST" |
| 13 | MISSION BAY
STYLE | | 41 | 3S12" GRA | SV-1-T | 68 | | SP-1-T | 6 | | 41 3 SECTION (RT), F/I R3-5 RIGHT TURN ONLY SIGN |
| 14 | MISSION BAY
STYLE
W/30' MA | | 63
32
64 | 3S12"
3S12" LA(PV)
3S12" | SV-2-T
MAT | | | | | | |
| 15 | 17-3-100
W/15' MA |
120V/
150W | 26+OLA
42
43 | 3S12"(PV)
3S12" GRA
3S12" GRA | SV-3-T
SV-2-T
MAT | | | | | | #4 3 SECTION (RT), F/I LEFT LANE 1-280 SB ONLY SIGN |
| 16 | 1-A | | 36
36 | 3S12"
LA | TV-1-T | | | | | | |
| 17 | 1-A | | 33 | 3S12" LA(PV) | TV-1-T | | | | | | |
| 18 | 1-A | | 63 | 3S12" LA(PV) | TV-1-T | | | | | | |

☐ EXIST. TO BE REMOVED AND SALVAGED

☒ EXIST. TO REMAIN

☒ FURNISH AND INSTALL NEW POLE AND EQUIPMENT

NOTE:
⚠ SEE ELECTRICAL LIGHTING PLANS FOR DETAILS

AS-BUILT

[illegible]